

Model 7010B



High Voltage Capacitance Bridge

- Automatic Self Balancing
- Current Comparator Technology
- 3-4 Terminal Measurements
- Lead Compensation Circuit
- Overall Accuracy 15 ppm
- Range Extension Option with 7020H

MODEL INFORMATION

The Model 7010B offers a wider capacitance range and increased voltage sensitivity. Minimum voltage sensitivity for full scale accuracy is 100 volts. The 7010B is a microprocessor controlled, metrology based, high voltage capacitance bridge. Its operation is fully automatic. A large vacuum florescent display presents relevant measuring quantities such as capacitance (C_x) and dissipation factor ($\tan\delta$). Easy to use front panel keyboard menus allow the operator to select the number of readings for statistical analysis of uncertainty calculations at the 95% ($2s$) level. All measured parameters can be transmitted over the IEEE488 interface for storage to a computer.

The model 7010B is a capacitance bridge with a ratio of 1000:1 making it ideal for both low and high voltage applications. The automatic self-balancing feature facilitates the use of the bridge for accurate load loss measurements of large high voltage inductive loads.

The 7010B may also be used for calibration of precision standard capacitors, tan-delta measurements and of precision potential transformers. Overall accuracy is <15 ppm in magnitude and phase. The technology is based on the two-stage-current-comparator-principle.

The 7010B has a capacitance ratio up to 1000:1 and dissipation (loss tangent) of 0 to 10% with a resolution of 1 ppm. To accommodate capacitance ratios larger than 1000:1 an additional two stage range extender, model 7020H, may be added to increase the ratio to 2,000,000:1. All connections are made on the rear of the instrument. The model 7010B is fully protected against transients.

The effect of lead and winding impedance on the measurement accuracy has been reduced by means of a built-in lead compensation circuit.

Applications:

Shunt Reactor Loss Measurements	Power Transformer Measurements
Calibration of Potential Transformers	Calibration of Low Voltage Std. Capacitors
Calibration of High Voltage Dividers	Calibration of High Voltage Power Capacitors
Inductance Measurements	Measurement of Low Loss, High Voltage Power
Loss Tangent Measurements to 10%	Corona Loss Measurements
Insulator and Dielectric Testing	

Specifications:

Capacitance Range	Cs: 10 pF to 10,000 pF Cx: 10 pF to 10,000,000 pF (10 uF)
Capacitive Ratio 1:1 to 1000:1	Ns: 0 to 1.11110 in steps of 0.000001 Nx: 1 to 1000 in steps of 1, 2, 5
Primary Current	10 Amp Maximum
Secondary (Cs) Current Range	1uA to 10mA
Dissipation Factor Range	0 to 10% in steps of 0.000001
Inductance Range	700mH to 700000H (Q factor > 10)
Test Frequencies	50 and 60 Hz
Accuracy	Ratio: ± 15 ppm for all Cx Ratios
Loss Angle	±1% of Reading ±10 ppm
Display	Large Vacuum Florescent
Reading Update	1 Second
Warm Up Time	< 5 Minutes to Full Rated Accuracy
Operating Environment	18 to 34°C, 10 to 80% RH
Operating Power	100, 120, 220, 240V - 50/60 Hz
Product Details	
Dimensions	545 x 435 x 355 mm
Weight	41 kg
Shipping Weight	50 kg
Warranty	1 Year Parts & Labor

Form MI 66, Rev. 6, Dated 09-0-03 (QAP19, App. "N")

Data Subject to Change- Rev3, 4/10

MI-Canada

Measurements International Ltd
PO Box 2359, 118 Commerce Drive
Prescott, Ontario, Canada K0E 1T0

Toll Free: 1-800-324-4988

Phone: (613) 925-5934
Fax: (613) 925-1195
Email: sales@mintl.com

MI-USA

Measurements International Inc.
815 Eyrie Dr Unit #4
Oviedo, FL 32765

Toll Free: 1-866-684-6393

Phone: (407) 706-0328
Fax: (407) 706-0318
Email: sales@mintl.com

MI-China

Room 4011, Anzhen Plaza
2 Andingmenwai Street
Dongcheng District
Beijing, China, 100013

Phone: 86 10 5127 8576
Fax: 86 10 5127 8532
Email: sales@mintl.com

www.mintl.com

MI-Europe

Druzstevni 845
686 05 Uherske Hradiste
Czech Republic

Phone: (420) 572 572 801
Fax: (420) 572 572 358
Email: sales@mintl.com

